

=====
Nortel Networks

Updated: 05/26/2004

=====
NETWORK CONFIGURATION MANAGER PATCH RELEASE SUMMARY:
=====

This is the 3.6.0.1 patch release for Network Configuration Manager 3.6. This patch resolves the Trim Archive wizard issue.

The Trim Archive wizard, available under the File Management folder, trims the number of archives for each device on which it is run. It is provided to help keep your archived files from growing without bounds by efficiently maintaining a current set of archives without having to manually delete aged archive files.

In NCM 3.6, the Trim Archive wizard runs correctly only when used on one device. If used on multiple devices, as when a folder is selected, the wizard incorrectly deletes archives from the devices contained in the folder and you will lose more archived data than originally specified. For most devices within the selection, ALL of the archive files will be erroneously deleted.

By applying the 3.6.0.1 NCM3.6 patch to the NCM server, the Trim Archive wizard will work as intended. For example, if the user has configured the Trim Archive wizard to keep 2 archives, then only the two most recently archived files will be kept for all of the devices in the selection. Only superfluous archives for the selected devices, ie archives exceeding the specified number of archives to be kept, will be trimmed.

2) PLATFORMS SUPPORTED:
=====

Windows NT 4.0, 2000, and XP Professional
Solaris 2.8

3) NOTES FOR INSTALLING THE PATCH:
=====

Solaris users should install the **ncm3601patch.bin** file.

Windows and XP users should install the **ncm3601patch.exe** file.

The same patch is used regardless of whether your NCM server supports 250, 1000 or 2000 BCMs.

- 3.1) **IMPORTANT:** Network Configuration Manager 3.6 must already be installed before attempting to apply the patch.
- 3.2) Download the patch from the Nortel Networks support web page to your system.
- 3.3) Copy the ncm3601patch.exe or ncm3601patch.bin file to a directory outside of the NCM install directory.
- 3.4) Stop the NCM Server or Service, if it is running.
- 3.5) Double-click the .exe file to run the installer on Windows systems.
or
Run the **./ncm3601patch.bin** command to run the installer on Solaris systems.
- 3.6) Follow the instructions on the installer screens. When installation is complete, click Finish.
- 3.7) Start the NCM Server or Service.
- 3.8) After installation is confirmed, you can delete the **ncm3601patch.exe** or ncm3601patch.bin file from your system.

4) NOTES FOR UNINSTALL:

=====

- 4.1) This patch can only be removed by uninstalling and reinstalling the NCM 3.6 product.

(c) 2004 Nortel Networks Incorporated. All rights reserved.